

CAR-4 Controls

1st Priority	Reverse Camera (Blue wire)							
	ON (12V)				OFF (0V)			
2nd P.	Hand Brake (Green wire)				Hand Brake (Green wire)			
	X		X		UP (0V)		DOWN (Floating)	
Lowest P.	Toggle Switch		Toggle Switch		Toggle Switch		Toggle Switch	
	X	X	X	X	Convert (open)	Bypass (short)	X	X
Output	V2 Reverse Camera				V1 DVD Player	Bypass GPS	Bypass GPS	

X : Don't care

RGB out: DB9 Pin configuration

Gray: PIN 1 — GND

Brown: PIN 2 — Sync of source 1

Red: PIN 3 — RED out

Yellow: PIN 4 — RED in from source 1

Green: PIN 5 — Green in from source 1

Blue: PIN 6 — Green out

Purple: PIN 7 — Blue out

Orange: PIN 8 — Blue in from source 1

Black: PIN 9 — Sync out

Source 1: Loop-through RGB/S input.

Source 2: Video input.